Automatic Computer Controlled combined Bond & Loop Test Unit

Model BLTU - Bond & Loop Test Unit

PROVEN AUTOMATIC ELECTRICAL TESTING SOLUTIONS







DESCRIPTION

The MK BLTU is a portable unit for measuring the resistance of bonding points on large structures. It is ideally suited to the the high-specification requirements of aircraft bond testing procedures.

MAIN FEATURES

- Tough polypropylene enclosure
- · Flip-off protective lid
- LCD 8" Touchscreen integrated monitor
- Smart Li-Ion batteries 'hot-swappable'
- Lightweight
- Carrying handle
- · Soft-start current source prevents arcing

- · On-screen instructions
- Auto and manual modes
- Wireless data upload & download
- Fast startup
- USB port
- Network Port

BOND TEST MEASUREMENT

Current (DC) Programmable 1mA to 2000mA

Resistance Range $0.2m\Omega$ to 2Ω Resistance resolution $0.1m\Omega$

Resistance Accuracy 1% ±0.2mΩ @ 2000mA

LOOP TEST MEASUREMENT

 $\begin{array}{lll} \text{Current (AC)} & 1 \text{Arms} \\ \text{Frequency} & 1 \text{kHz} \\ \text{Resistance Range} & 1 \text{m}\Omega \text{ to } 200 \text{m}\Omega \\ \text{Resistance resolution} & 0.1 \text{m}\Omega \\ \text{Resistance Accuracy} & 1\% \pm 0.2 \text{m}\Omega \end{array}$

SYSTEM OPTIONS

Temperature compensation 10Amp Bond Current

DIMENSIONS

 Length
 270mm (10.63")

 Depth
 246mm (9.69")

 Height
 124mm (4.88")

 Weight
 <4kg</td>

Under the MK Test Systems Continuous Improvement Programme, specifications are subject to change.

www.mktest.com

sales@mktest.com

tel. +44(0)1823 661100


fax. +44(0)1823 661160



Automatic Computer Controlled combined Bond & Loop Test Unit















Automatic Computer Controlled combined Bond & Loop Test Unit

Panel PC Control

- All functions controlled via MK software.
- Automatic control of test process

Combined Bond and Loop Tester

Battery Powered

No mains cable required during operation

Hot Swap Battery

- 2 Battery ports, hot swap function to eliminate downtime
- Optimised power efficiency to prolong battery life

Portable

Compact and lightweight for single person operation.

Rated accuracies to meet most demanding Aerospace requirements

Manual Mode

Automatic Mode

- Automatic download of test requirement
- Automatic creation of test sequence / Test programme
- Simple Step-by Step graphical operator instruction
- Automatic logging and upload of test results

Active Probe, increased automation

- On-Probe LED indication of test status
- On-Probe push button to step through test progress
- No need to touch test unit during automatic test process

Probe and Clamp recognition

System ensures correct clamps and probes used


Automatic progress through test

Software controlled Calibration

Calibration can be carried out by customer using MK calibration kit



Automatic Computer Controlled combined Bond & Loop Test Unit






Software




Login



Manual mode Bond & Loop Test



Download test requirement data



Automatic test mode progress screen





Test Hand Wing Test Point

LOOKING OUTBD ON RIB6

BB0054

EB0054

AFT

Automatic test mode Operator Guidance Screens



Active Bond Test Probes







The Active Bond Test Probes indicate the Pass or Fail status of a test via the Green and Red LEDs.

The Pushbutton on the rear of the probe allows the operator to accept a test result and progress to the next test, without touching the test unit itself.



Calibration









	Part Number	Description
	BLT-033	MK Test Systems BLTU Bond and Loop Test Unit
September 2000 to 10 to	BLT-0730	Additional Batteries
	BLT-0731	Battery Charger Unit
	BLT-0702	Active Bond Test Probes 2 per set NOTE. Customised and application specific probes and clamps
	BLT-0706/7	available. Long nose probes, clamps for large diameter cables etc. Ask MK for details. 1 Inject clamp per set (part BLT-0706) 1 Detect clamp per set (part BLT-0707)
	BLT-0732	BLTU Data Adaptor Enables USB and Ethernet connectivity
	BLT-0230	Calibration Kit Enables the end user to calibrate the BLTU

